

# WAC LIGHTING

## 120V/24V 60W Plug-In Electronic Transformer

### Class 2 Power Supply

Fixture Type: \_\_\_\_\_

Catalog Number: \_\_\_\_\_

Project: \_\_\_\_\_

Location: \_\_\_\_\_

#### Model & Product

EN-2460-P-AR Plug-in Electronic Transformer with Open Splice 120V Input 24V Output 60 Watt

#### L x W x H

2.75IN x 1.625IN x 1.75IN

Example: **EN-2460-P-AR**

#### DESCRIPTION

Low Voltage plug-in Class 2 electronic transformer designed to be used as a plug-and-play style transformer. Contains an on/off toggle switch at the base and a 72" detachable cord with an open splice. Inherently protected and power limited, protecting the lighting system from both normal and abnormal short circuits. Built-in auto reset, soft start, short and overload circuit protection features. The soft start delayed start feature extends lamp life by delaying the abrupt inrush current to the lamp. Ideal for WAC Lighting under cabinet systems.

#### FEATURES

- 1W minimum load
- UL listed Class 2 plug-in electronic transformers
- Plug-in power supply with on/off switch and 6' detachable cord
- Class 2 transformers are required for most cabinet listed fixtures
- Inherently protected and power limited, protecting the lighting system from both normal and abnormal short circuits.
- Built-in auto reset, soft start, short and overload circuit
- 5 year warranty

#### SPECIFICATIONS

**Construction:** Polycarbonate  
**Input:** 120 VAC, 50/60Hz  
**Finish:** Black  
**Operating Temp:** °F to °F (°C to °C)  
**Standards:** UL, cUL, Dry Location Listed



#### FINISHES



Black

# WAC LIGHTING

## 120V/24V 60W Plug-In Electronic Transformer

Class 2 Power Supply

Fixture Type: \_\_\_\_\_

Catalog Number: \_\_\_\_\_

Project: \_\_\_\_\_

Location: \_\_\_\_\_

---

### ACCESSORIES

---

	<i>Model</i>	<i>Description</i>	<i>Finish</i>
	<b>MTB-01</b>	<i>Multiple Terminal Block</i>	<i>Black</i>